



The FMS5, 10 and 20 Fireman's Microphone Stations each comprise a lockable wall-mounting box, housing a fist microphone and associated electronics, and are designed to work with the whole range of ASL Voice Alarm Systems.

The FMS5 provides 5 zone selection capability whilst the FMS10 and 20 provide 10 and 20 zones respectively, while, instead of zone selection, any of the buttons may be configured to broadcast pre-recorded messages. The FMS5-20 will operate in an all-call mode even in the event of processor failure within the router, as required by BS5839 Pt 8. In this instance, the 'All Call Only' LEDs will illuminate to indicate the restricted function.

An in-built signal limiting automatic gain control is provided to help compensate for varying operator technique. A processor within the Fireman's Microphone Stations interfaces all LEDs and switches to the DSP Router by means of a serial interface, while microphone audio is provided as a balanced 0 dBu (nominal) analogue signal. The microphone's processor is also responsible for generating an outgoing low-frequency surveillance tone which is used to monitor the audio connection to the VAR Router, while microphone capsule monitoring is performed by injection and monitoring of a signal such that either open or short circuit of the capsule or associated wiring will indicate a fault.

Hardwired connections are provided for the PTT switch and 'Speak Now' and 'All Call Only' LEDs. This cabling is continuously monitored by the router for open and short circuits. Field connections are provided by internal DIN rail mounted terminals. Top and bottom cable entry points are provided. Rear cable entry is also catered for by means of 'knock-outs' in the rear of the box.

For further details, and for information on other products, please visit www.asl-control.co.uk.

SPECIFICATION

General

Supply Voltage Range	18 – 40 V DC
Current Consumption Maximum - all LEDs on	
FMS5	75 mA @ 24 V DC supply
FMS10	80 mA @ 24 V DC supply
FMS20	90 mA @ 24 V DC supply
Current Consumption Maximum - Quiescent	
FMS5 / FMS10 / FMS20	64 mA
Format.....	Wall mounting box
Fire Microphone Facility	BS5839 Pt 8 compliant
Microphone	Fist
Zone Select Buttons (can also control routes or DVAs)	
FMS5	5
FMS10	10
FMS20	20
Other Buttons.....	PTT button on fist microphone
LEDs	2 LEDs per zone Select button (zone Busy and zone Selected)
	All Call Only (twin)
	Speak Now (twin)
	Status
Colour	Red RAL3020

Dimensions and Weight

Dimensions (H x W x D).... 300 mm x 350 mm x 88.5 mm
(excluding handle)

Weight

FMS5 / FMS10.....	5.7 kg
FMS20	5.9 kg

Environmental

Temperature (Storage and Operating).... -5 °C to +50 °C
Humidity Range

0% to 93% Non-condensing



This equipment is designed and manufactured to conform to the following EC standards:

EMC EN 55103-1/E1, EN 55103-2/E5

Safety EN60065

Manufacturer

Application Solutions Limited

Head Office: The Riverside Centre - Railway Lane - Lewes - East Sussex - BN7 2AQ - UK

Tel: +44(0)1273 476608

Fax: +44(0)1273 478888

Voice Alarm Direct: Tel: +44(0)1273 405411

Fax: +44(0)1273 405415

www.asl-electronics.co.uk

All rights reserved.

Information contained in this document is believed to be accurate, however no representation or warranty is given and Application Solutions Limited assumes no liability with respect to the accuracy of such information.



QUALITY ASSURED FIRM
CERTIFICATE NUMBER 0430449401